

Electronic Whiteboard

UB-5325 UB-5825 UB-7325




Panaboard takes notes instead of you Improves your Presentations and meetings


- Plain paper printing with multiple copies.
- Panaboard can work as a PC printer.
- Panaboard can be controlled from PC.
- Panaboard increases efficiency and reduces meeting time.
- Panaboard can be wall-mounted or used with floor-stand option.







PC Interface



Quick Image Navigator

Scanned data can be quickly displayed and edited. All information can be organized into folders for easy management, and the contents of the folders can be checked by viewing thumbnail displays.

You can easily edit, print or distribute the scanned

Data Library

Printer Driver

The Panaboard can also work as a PC printer. In a meeting, if you need to print out some documents, the Plug & Play of USB makes it easy to print out documents from the Panaboard.





1 Screen can also be used for the Projector. (UB-7325)

TWAIN Driver



By just one click, you can scan the image on the Panaboard screen as image data to your computer and from your computer, you can control the

Panaboard function just like operating the Panaboard control panel.

General	Model number	UB-5325	UB-5825	UB-7325
Power Supply		AC 100 - 120 V, 50/60 Hz or AC 220 - 240 V, 50/60 Hz		
Power Consumption (Operational)		1.40 A (AC 100 - 120 V) or 0.75 A (AC 220 - 240 V)		
External Dimensions (Height X Width X Depth, without stand)		1,396 mm X 1,550 mm X 230 mm	1,396 mm X 1,912 mm X 230 mm	1,396 mm x 1,648 mm x 264 mm
Weight (without stand)		36.0 kg	38.5 kg	42.5 kg
Input Block				
Panel Dimensions (Height X Width)		900 mm X 1,400 mm	900 mm X 1,762 mm	900 mm X 1,400 mm
Panel Surface		2 (endless type)		4 (endless type)*1
Copying Area (Height X Width)		850 mm X 1,330 mm	850 mm X 1.692 mm	850 mm X 1,330 mm
Scanning System		,	Image sensors	, , , , , , , , , , , , , , , , , , , ,
Output Block				
Printing System		Fusion thermal transfer type		
Copy Paper		Standard or recycled paper (60-90 g/m²)		
Copy Paper size		A4 or Letter		
Copy Density		203 dpi (8 dots/mm)		
Copy Color		Black		
Time Required for	Copying	15 sec./sheet		
Continuous Copies				
Contrast Adjustment		Two levels : Normal/Dark		
2-screen Compressed Copying			Yes	No
System Requir	ements			
Computer		IBM® PC/AT or compatible machine with a CD-ROM drive		
CPU		Pentium® II or higher processor		
Interface		USB 1.1 or USB 2.0 (This electronic board functions with USB 1.1.)		
Operating System		Windows Vista® (32 bits)*2, Windows® XP, Windows® 2000, Windows® 98, Windows® Me		
Memory		Windows® 98/Me: 64 MB or more, Windows® 2000: 128 MB or more,		
		Windows® XP: 256 MB or more, Windows Vista®: 512 MB or more		
Hard Disk		At least 240 MB free space (except saving space for image file)		
Accessories				
		Operating instructions, Installation mar A4 or Letter Size Paper for test (20 she		red and blue, one each) • Software CD-ROM • Eraser (one po
Optional Equip	ment			
Wall-Mounting Kit		KX-B063		
Stand		KX-B061		
Separately Ava	ilable			
Replacement film	UG-6001 (Set of 2 rolls [50 m])			
Markers		KX-B031 (set of 10 black markers), KX-B032 (set of 10 red markers), KX-B033 (set of 10 blue markers)		
Erasers		KX-B042 (set of 6 erasers)		
Marker and Eraser Set		KX-B035 (contains 1 black, 1 red and 1 blue markers and 1 eraser)		



Please download the latest printer driver and application for Windows Vista® from the following web site:

http://panasonic.co.jp/pcc/products/en/eboard/download/index.html



UB-5325 2-Screen Standard size





UB-7325 4-Screen Standard size

(Stand option)

- Note:

 Microsoft, Windows and Windows Vista are either registered trademarks or Windows is Microsoft Corporation in the United States and other countries.

 Windows is Microsoft® Windows® operating system.

 IBM is a registered trademark of International Business Machines Corporation.

 Pentium is a registered trademark of Intel Corporation in the U.S. and other countries.

- All trademarks referred to in this catalog are property of their respective companies.

http://panasonic.net/pcc/eboard/